

Qualified PC Notebooks for Avid Media Composer, Avid Xpress Pro & Avid NewsCutter XP

Qualified PC Notebooks	Summary	Fullscreen Playback	Avid MOJO or MOJO SDI	Avid Unity MediaNetwork Ethernet (including LANshare)	Avid Unity MediaNetwork FibreChannel	Avid Unity ISIS	Notes
HP Compaq 8510w Mobile Workstation	2.20 GHz Core 2 Duo processor, 4MB L2 Cache, 800Mhz FSB, 2 GB 667 MHz DDR2 SDRAM, NVIDIA Quadro FX 570M graphics, with up to 256MB, 80 GB 7200 rpm SATA		√	√		√	Requires :- Media Composer v2.7.x NewsCutter v6.7.x Xpress Pro v5.7.x
HP Compaq 8710w Mobile Workstation	2.4 GHz Core 2 Duo processor, 4MB L2 Cache, 800Mhz FSB, 2 GB 667 MHz DDR2 SDRAM, NVIDIA Quadro FX 1600M graphics, with 256MB, 80 GB 7200 rpm SATA		√	√		√	Requires :- Media Composer v2.7.x NewsCutter v6.7.x Xpress Pro v5.7.x
HP Compaq nw9440 Mobile Workstation	2.16GHz min Core Duo or Core 2 Duo NVIDIA Quadro FX1500M with 256MB of video memory 2GB memory 80 or 100GB, 7200 RPM internal drive	√	√	√		√	- 1.67 GHz processors also supported for SD - Supports DVCPRO HD (DV100) and all Avid formats - If using ISIS with the 9440: a.) Use the onboard Broadcom Network Interface Card b.) Change the RxStdDescCnt registry from 200 to 511
HP Compaq nw8440 Mobile Workstation	2.16GHz min Core Duo or Core 2 Duo processor for HD ATI Mobility FireGL V5200 Graphics 2GB System Memory 7200 RPM SATA Hard Drive	√	√	√		√	- 1.67 GHz processors also supported for SD - Supports DVCPRO HD (DV100) and all Avid formats. - Requires Avid Xpress Pro v5.5 or later, prior versions of Avid Xpress Pro are not supported.

Qualified PC Notebooks for Avid Media Composer, Avid Xpress Pro & Avid NewsCutter XP

Qualified PC Notebooks	Summary	Fullscreen Playback	Avid MOJO or MOJO SDI	Avid Unity MediaNetwork Ethernet (including LANshare)	Avid Unity MediaNetwork FibreChannel	Avid Unity ISIS	Notes
Dell Precision M6300 Mobile Workstation	2.4 GHz Core 2 Duo processor, 4MB L2 Cache, 800Mhz FSB, 2 GB 667 MHz DDR2 SDRAM, NVIDIA Quadro FX 1600M graphics, with 256MB, 80 GB 7200 rpm SATA		√	√		√	
Dell Precision M65 Mobile Workstation	Intel Core Duo or Core 2 Duo processor 2.16 GHz min for HD 2GB Memory 7200 rpm SATA hard drive NVIDIA Quadro FX350M	√		√		√	- 1.67 GHz processors also supported for SD - If using ISIS with the M65: a.) Use the onboard Broadcom Network Interface Card b.) Change the RxStdDescCnt registry from 200 to 511
Dell Precision M90 Mobile Workstation	Intel Core Duo 2 processor 2.16 GHz min for HD 2GB Memory 7200 rpm SATA hard drive NVIDIA Quadro FX 2500M / 1500M	√	√	√		√	- 1.67 GHz processors also supported for SD - 2.16 GHz minimum for HD
Dell Precision M70 Mobile Workstation	2 GB of 533MHz, DDR2 SDRAM; NVIDIA Quadro FX Go1400 256MB graphics controller)			√		√	-Requires add-on IEEE-1394 card - A 60 GB 7200 RPM internal drive should be used with this model. - DVCPRO HD format not supported. - Avid Mojo is not supported with this laptop; connecting it will result in corruption of the firmware and render the Avid Mojo unusable
HP Compaq nx9600 Notebook PC	Minimum 3.2GHz P4 for DVCPRO HD 2 GB of 400 MHz, DDR SDRAM ATI Mobility Radeon X600 (PCI Express) with 128MB of video memory		√	√		√	- A 60 GB 7200 RPM internal drive is recommended with this model. - A 5400 RPM drive is supported but will result in fewer video streams. - Supports Avid Unity LANshare EX if Avid Mojo is NOT connected - Not currently supported with Avid Xpress Pro v5.5.x or later. (Requires Avid Xpress Pro v5.2.x or earlier)
Dell Inspiron 5160	3.2GHz Pentium 4 with hyper-threading.		√	√	√	√	- Includes integrated graphics and 1394 port

Qualified PC Notebooks for Avid Media Composer, Avid Xpress Pro & Avid NewsCutter XP

Qualified PC Notebooks	Summary	Fullscreen Playback	Avid MOJO or MOJO SDI	Avid Unity MediaNetwork Ethernet (including LANshare)	Avid Unity MediaNetwork FibreChannel	Avid Unity ISIS	Notes
HP Compaq Mobile Workstation nw8000			√	√			Add-in PCMCIA cards are not supported. - Supports Avid Unity LANshare EX if Avid Mojo is NOT connected
Dell Precision M60 Mobile Workstation			√	√			- A 60 GB 7200 RPM internal drive should be used with this model. - Supports Avid Unity LANshare EX if Avid Mojo is NOT connected

Please Note:

- Notebook systems may not deliver the performance required to support some resolutions.
- Notebook PCs used with Avid Mojo or Avid Mojo SDI must contain an integrated 1394 port. Avid Mojo must be connected to the integrated 1394 port and not to a port provided by an add-in PCMCIA card. Avid Mojo is not supported in notebook PCs using any PCMCIA card.
- Avid Mojo or Mojo SDI not supported with Avid Unity or Avid ISIS connected notebooks
- Avid Mojo or Mojo SDI supported only with internal ATA (IDE) or serial ATA storage
- Avid Mojo SDI requires v5.5 or higher