

## Qualified PC Workstations for Avid Xpress Pro, Avid Media Composer and Avid NewsCutter

Qualified PC Workstations	Summary	Mojo/SDI, Adrenaline/ Dnxccl	Avid Unity MediaNetwork Ethernet (including LANshare)	Avid Unity MediaNetwork FibreChannel	Avid Unity ISIS	Notes
HP xw8400	2.33, 2.66 GHz or 3.00 GHz Dual Quad-Core Xeon	√	√	√	√	<ul style="list-style-type: none"> <li>- Requires editor release x.7 or greater.</li> <li>- Supports the NVIDIA Quadro FX 1500 and 3500 on DNA hardware and software systems.</li> <li>- Requires separate IEEE-1394 card (FW232-06, HP part number P997A), do not use built-in port for DNA connections.</li> <li>- Requires 4GB system RAM, configured as 4 separate 1GB DIMMs.</li> </ul>
HP xw8400	2.66 GHz or 3.00 GHz Dual Dual-Core Xeon	√	√	√	√	<ul style="list-style-type: none"> <li>- Requires editor release x.2.10 or greater.</li> <li>- Supports the NVIDIA Quadro FX 1500, 3450 and 3500 on DNA-hardware systems.</li> <li>- Supports the NVIDIA Quadro FX 1500 or 560 on software systems.</li> <li>- Requires ATTO UL4D SCSI card.</li> <li>- For configuration details see the <a href="#">Avid HP xw8400 Configuration Guidelines</a></li> </ul>
HP xw8200	3.40 GHz or 3.66 GHz Single or Dual Xeon	√	√	√	√	<ul style="list-style-type: none"> <li>- For configuration details see the <a href="#">Avid DNA HP xw8200 Configuration Guidelines</a></li> </ul>
HP xw8000	3.06 GHz or 3.20 GHz Dual Xeon	√	√	√	√	<ul style="list-style-type: none"> <li>- Supports the NVIDIA Quadro FX 1100 on DNA hardware and software systems.</li> <li>For configuration details see the <a href="#">Avid HP xw8000 Configuration Guidelines</a></li> </ul>
HP xw4600	3.00 GHz Core 2 Duo	√	√		√	<ul style="list-style-type: none"> <li>- Requires editor release x.7 or greater.</li> <li>- Supports the NVIDIA Quadro FX 570 on software systems.</li> </ul>

## Qualified PC Workstations for Avid Xpress Pro, Avid Media Composer and Avid NewsCutter

Qualified PC Workstations	Summary	Mojo/SDI, Adrenaline/ Dnxccl	Avid Unity MediaNetwork Ethernet (including LANshare)	Avid Unity MediaNetwork FibreChannel	Avid Unity ISIS	Notes
HP xw4400	2.13 GHz or 2.40 GHz Core 2 Duo	√	√	√	√	<ul style="list-style-type: none"> <li>- Requires editor release x.2.10 or greater.</li> <li>- Supports the NVIDIA Quadro FX 1500, 3450 and 3500 on DNA hardware systems.</li> <li>- Supports the NVIDIA Quadro FX 1500 or 560 on software systems.</li> <li>- Requires ATTO UL5D SCSI card.</li> <li>- For configuration details see the <a href="#">Avid HP xw4400 Configuration Guidelines</a></li> </ul>
HP xw4300	3.20 GHz Pentium 4	√	√		√	<ul style="list-style-type: none"> <li>- Support for NewsCutter only.</li> </ul>
Dell Precision 670	Dual Xeon 3.0 GHz (or faster)	√	√	√	√	<ul style="list-style-type: none"> <li>- For configuration details see the <a href="#">Avid Mojo Dell 670 Configuration Guidelines</a></li> </ul>
Dell Precision 490	2.66 GHz or 3.00 GHz Dual Dual-Core Xeon	√	√	√	√	<ul style="list-style-type: none"> <li>- Requires editor release x.2.10 or greater.</li> <li>- Supports the NVIDIA Quadro FX 3500.</li> <li>- For configuration details see the <a href="#">Avid Dell 490 Configuration Guidelines</a></li> </ul>
Dell Precision 390	2.40 GHz or 2.67 GHz Core 2 Duo	√	√		√	<ul style="list-style-type: none"> <li>- Supports the NVIDIA Quadro FX 550</li> <li>- Requires ATTO UL5D SCSI card.</li> <li>- For configuration details see the <a href="#">Avid Dell Precision 390 Configuration Guidelines</a></li> </ul>